

**2025 California Building Standards Code of Regulations Title 24**

**RESIDENTIAL ELECTRICAL LOAD  
WORKSHEET**

Contractor Name \_\_\_\_\_ Project Address \_\_\_\_\_  
 Contractor License # \_\_\_\_\_

**Method for determining the electrical load and sizing of the electrical service:**

CEC Section: 220.82 "Optional Feeder and Service Load Calculations"

- |  |   |                    |
|--|---|--------------------|
| General light, power _____ SF x 3 volt-amperes   | = | _____ volt-amperes |
| Kitchen appliance circuits (minimum 2 @ 1,500 volt-amperes)  | = | _____ volt-amperes |
| Laundry circuits (minimum 1 @ 1,500 volt-amperes)  | = | _____ volt-amperes |
| Electric range (NP rating)   | = | _____ volt-amperes |
| Wall mounted oven (NP rating)  | = | _____ volt-amperes |
| Water heater (NP rating)   | = | _____ volt-amperes |
| Dishwasher (NP rating)   | = | _____ volt-amperes |
| Disposal (NP rating)   | = | _____ volt-amperes |
| Dryer (NP rating)  | = | _____ volt-amperes |
| Other (examples: Permanently connected motors, appliances fastened in place, electric vehicle charger) | = | _____ volt-amperes |

**Sub Total A** (Add all loads listed above) = \_\_\_\_\_ volt-amperes

The first 10,000 volt-amperes is calculated at 100% = 10,000 volt-amperes  
 The remaining volt-amperes are calculated at 40% = \_\_\_\_\_ volt-amperes

**Total A:** Sub Total A \_\_\_\_\_ -10,000= \_\_\_\_\_ x.40= \_\_\_\_\_ +10,000= \_\_\_\_\_ volt-amperes

**Heating and Air-Conditioning** (The Largest of the following shall be included):

1. Air conditioning and cooling (100% NP rating) = \_\_\_\_\_ volt-amperes
  2. Heat pump without supplemental heating (100% NP rating) = \_\_\_\_\_ volt-amperes
  3. Heat pump with supplemental electric heating (100% NP rating plus 65%) = \_\_\_\_\_ volt-amperes
  4. Electrical space heating < 4 separate units (65% NP rating) = \_\_\_\_\_ volt-amperes Electrical
  5. space heating ≥ 4 separate units (40% NP rating) = \_\_\_\_\_ volt-amperes Electrical thermal
  6. storage and other (100% NP rating) = \_\_\_\_\_ volt-amperes
- Total B:** Largest Heating and Air Conditioning Load (From Above) = \_\_\_\_\_ volt-amperes

Calculate Total Service Load:

**Total A** \_\_\_\_\_ + **Total B** \_\_\_\_\_ ÷ 240 volts = \_\_\_\_\_ (amps size for service entrance conductors and panel)

## **Sample Residential Electrical Load Calculation – Step by Step Example (Optional Method) CEC 220.82**

2800 sq. ft. home 12 kW range

3 kW water heater

5 kW clothes dryer

1.5 kW dishwasher

6.96 kW air conditioning

### **Step 1:**

Multiply the sq. ft. area by 3 VA per Sq. ft.

2800 sq. ft. X 3 VA = 8,400 VA (VA = volt-amperes)

### **Step 2:**

Add 1500 VA for each 2-wire, 20-amp small appliance branch circuit and each laundry circuit. 1,500

VA X 3 = 4,500 VA

### **Step 3:**

Add in the appliance loads at nameplate value.

Range 12,000 VA

Water heater 3,000 VA

Clothes dryer 5,000 VA

Dishwasher 1,500 VA

EV Charger: 7,000 VA

### **Step 4:**

Calculate general loads by adding steps 1, 2, and 3:

8,400 VA (Lighting)

4,500 VA (Small appliance/laundry circuits)

12,000 VA (Range)

3,000 VA (Water Heater)

5,000 VA (Dryer)

1,500 VA (Dishwasher)

7,000 VA (EV Charger)

Total= 41,400 VA

### **Step 5:**

Take the first 10 kW at 100%. 10,000 VA

Take the remainder (31,400 VA) at 40%: 31,400 VA X .40 = 12,560 VA

### **Step 6:**

Add the two values from step 5 together to find the general load.

10,000 VA + 12,560VA = 22,560 VA

### **Step 7:**

Identify the single largest load identified from Heating and Air-Conditioning Load.

A/C load = 6.96 kW (From page 1, Total B)

### **Step 8:**

Add the general load to the largest of the AC or heating load.

General Load: 22,560 VA (Step 6)

A/C Load: 6,960 VA (Step 7)

Total Service Load= (22,560 + 6,960 = 29,520

### **Step 9:**

Divide the load in VA by the voltage. 29,520 / 240= 123A

**\*Nameplate ratings provided in watts can be converted to volt-amperes at a rate of 1:1. (Assumed power factor of 1) Example: A nameplate rating of 1 kW= 1,000**